

# VICTORY G40BS

50Hz@1500RPM 400/230V 3PH

**GENMAC**  
POWER PRODUCTS

 **Baudouin**  **STAMFORD**



Picture for illustration purposes only

## Overall performance

### G40BS

PRP Continuous power kVA	<b>40</b>
PRP Continuous power kW	<b>32</b>
LTP Stand-by power kVA	<b>44</b>
LTP stand-by power kW	<b>35</b>
Power factor cos φ <sub>lp</sub>	<b>0.8</b>
Voltage VAC	<b>400/230</b>
Frequency Hz	<b>50</b>
Ampere PRP/LTP	<b>58 / 63</b>
Speed RPM	<b>1500</b>

## Dimensions and noise level

Length mm	<b>2100</b>
Width mm	<b>930</b>
Height mm	<b>1280</b>
Net Weight kg	<b>820</b>
Gross Weight kg	-
Sound pressure at 7 mt dBA	<b>70.00</b>

## Data reference

Standard reference conditions temperature 25°C, altitude 1-1000m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850 gr/l. Power performance data as quoted can be obtained after the initial running-in period of the engine, during which one has to follow the instructions of the engine manufacturer as stated in the use and maintenance manual of the specific engine. The tolerance shown by the engine manufacturer is +/- 5%. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance. P.R.P. Prime Power-Continuous power at variable load: The power that a genset can supply in continuous service at a variable load for an unlimited number of hours per year while respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer. according to ISO8528-1. The average power supplied over time and any applicable overload must be less than the percentages stated by the Manufacturer. L.T.P. Limited-time running power-Limited power: The maximum power that a genset can supply for a limited time respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer according to ISO 8528-1. The number of hours per year is stated by the Manufacturer. Overload is not permitted.\*For reasons of transport and/or storage, liquids (oil and antifreeze) and batteries might not be included in the delivery.

**GENMAC**  
POWER PRODUCTS

 **MADE IN ITALY**

© 2017 GENMAC - P.I./VAT IT 01224860351 - cap. soc. € 100.000,00 i.v. / R.E.A. RE n.170570 - Reg. Imp. RE n.01524820402  
Export M/RE012315 -GENMAC S.r.l.s.u. is subject to management and coordination of IPG SpA - Milano/Odei/Merano/Verona  
Reg. Imp. n.12616930967

Page 1 of 2  
00-04/11/2021

# VICTORY G40BS

50Hz@1500RPM 400/230V 3PH

**GENMAC**  
POWER PRODUCTS

## Engine general data

Engine brand	<b>Baudouin</b>
Model	<b>4M06G44/5</b>
PRP Power kW	<b>37.00</b>
LTP Power kW	<b>41.00</b>
Fuel	<b>Diesel</b>
Nr. cylinders	<b>4</b>
Air intake	<b>Turbocharged</b>
Cooling	<b>Water</b>
Cubic capacity l.	<b>2.30</b>
Speed regulation	<b>Electronic</b>
Starting	<b>-</b>
Performance Class - steady state regulator accuracy +/- %	<b>---</b>
Load Step G1 - KWe	<b>-</b>
Load Step G2 - KWe	<b>-</b>
Load Step G3 - KWe	<b>-</b>
Voltage VDC	<b>12</b>
Emissions	<b>-</b>

## Alternator general data

Alternator brand	<b>Stamford</b>
Model	<b>S1L2-K1</b>
Type of excitation	<b>Self-excited</b>
Type of regulation	<b>AVR</b>
Regulator precision +/- %	<b>1.00</b>

## Structure data

Type of structure	<b>VICTORY</b>
Tank capacity l.	<b>90</b>
Retention basin	<b>not</b>
Exhaust diameter mm	<b>-</b>

## Control panel features

### QTVA-AMF5

Self-standing tower with metal box  
 Circuit breaker  
 AMF controller COMAP IntelliNano AMF5  
 - Voltmeter, Frequencymeter, Ammeter  
 - Generator power (kW, kV Ar, kV A & pf) monitoring  
 - Hour meter  
 - Fuel level meter  
 - Overload (kW & kV Ar) protection  
 - Low oil pressure protection  
 - High coolant temperature protection  
 - Low fuel level protection  
 - Battery charger alternator fault  
 - Rpm protection  
 Emergency stop button  
 Terminal board for ATS connection  
 Battery charger  
 Startin Key

## Fuel consumption

Consumption 25% l./h	<b>2.80</b>
Consumption 50% l./h	<b>4.70</b>
Consumption 75% l./h	<b>7.00</b>
Consumption 100% l./h	<b>9.50</b>
Autonomy at 75% of load h.	<b>≈ 13 h</b>

## Engine liquids and equipment

Type of lubricant	<b>Oil SAE 15W40</b>
Lubrication capacity l.*	<b>9.50</b>
Type of coolant	<b>Antifreeze liquid</b>
Coolant capacity l.*	<b>16.00</b>
Air intake filter	<b>-</b>
Battery capacity Ah	<b>70</b>
Number of batteries*	<b>1</b>

## Fuel system and energy balance

AC pump suction head kPa	<b>-</b>
Combustion air flow volume LTP m3/min	<b>2.22</b>
Cooling air capacity LTP m3/min	<b>84.30</b>
Exhaust gas flow-density LTP m3/min	<b>7.92</b>
Exhaust gas temperature LTP °C	<b>650.00</b>
Brake mean effective pressure kPa	<b>8.00</b>
Energy to exhaust LTP kWt	<b>-</b>
Energy to coolant LTP kWt	<b>-</b>
Energy to radiation LTP kWt	<b>-</b>



Dealer

**GENMAC**  
POWER PRODUCTS

MADE IN ITALY